# Slotted Conductor-Backed Coplanar Waveguide Antennas

 <sup>#</sup>Lieh-Chuan Lin<sup>1</sup>, Yi-Shyang Cheng<sup>1</sup>, Ruey Bing Hwang<sup>1</sup>, Toshihide Kitazawa<sup>2</sup>, Yu-De Lin<sup>1</sup>
<sup>1</sup>Department of Communication Engineering, National Chiao Tung University 1001 Ta-Hsueh Rd., Hsinchu 300, TAIWAN, cm\_doglin@hotmail.com
<sup>2</sup>Department of Electrical and Electronic Engineering, Ritsumeikan University 1-1-1 Noji-Higashi, Kusatsu, Shiga 525-8577, JAPAN, kitazawa@se.ritsumei.ac.jp

## **1. Introduction**

Conductor-backed coplanar waveguide (CBCPWs) is a commonly used waveguide structure in planar printed circuits. It was found out that CBCPW always leaks power in a surfacewave form of the background parallel-plate mode [1]-[3], since the phase constant of the guided CBCPW mode is always less than that of the background parallel-plate mode. In waveguide applications, this surface-wave leakage will cause power loss and coupling between neighboring lines, and should be avoided in the operating frequency band using various mode-suppression schemes [4]-[5]. However, in antenna applications, we can place radiating slots on the top conductor or the bottom conductor [6] along the propagation direction of the parallel-plate surface-wave, resulting in a slotted antenna array structure similar to the slotted waveguide antennas in [7] or the radial line slot antenna in [8]. In this paper, we have designed a novel fan-shaped slotted CBCPW antenna operating in Ku band. Its center frequency is 12 GHz and can be used in direct broadcast satellite (DBS) systems.

#### 2. Antenna Design

Fig. 1 illustrates the top view and the cross-sectional view of the antenna structure near the excitation port. For the CBCPW mode, the propagation constants,  $k_y = \beta - j\alpha$ , can be obtained by the spectral domain approach. They are shown in Fig. 2 with the designed parameters: the dielectric constant  $\varepsilon_r = 3.55$ , the substrate thickness h = 1.524 mm, the center feedline width S = 0.6 mm, and the gap width W=1mm. The propagation direction of the parallel-plate surface-wave mode,  $\theta$  in Fig. 1, can be approximately obtained by  $\theta = \cos^{-1}(\beta/k)$ , where  $\beta$  is the phase constant of the CBCPW mode and k is the phase constant of the parallel-plate mode. Along the propagation direction of the parallel-plate mode, we place radiating slots that are tilted an angle  $\phi$  from the propagation direction, as shown in Fig. 3. The power guided by the parallel mode can thus be radiated into the air through slots.

The tilt angle  $\phi$  controls the amount of the radiation power. The normalized radiation resistances versus the tilt angle  $\phi$  are shown in Fig 4, where the characteristic impedance  $Z_0$  of the parallel-plate unit cell is 16.73  $\Omega$ . Following the design procedure in [8]-[9], we can design a slot array with appropriate tilted radiation slots to achieve a high-gain antenna.

# **3. Measurement Results**

The antenna is designed on the Rogers 4003 substrate, with a dielectric constant  $\varepsilon_r = 3.55$ , a loss tangent tan $\delta = 0.0027$ , and the substrate thickness h = 1.524 mm. The CBCPW structure parameters are as follows: the center feedline width S = 0.6 mm, and the gap width W=1 mm, and the characteristic impedance of the CBCPW is 100  $\Omega$ . A section of tapered line is added to match the characteristic impedance of the 50  $\Omega$  SMA connectors. The geometrical parameters used for slots are: the slot width  $W_s = 0.5$  mm, the slot length  $L_s = 8.6$  mm, the distance between slots on the

same radial line  $L_g = 13.27$  mm. We put 16 rows of slots on both sides of the top ground plates.and the tilt angle has a minimum value  $\phi = 6.1^{\circ}$  at the first row according to Fig. 4. The tilt angle  $\phi$  is increasing from row to row. There are (17-*n*) slots on the *n*-th row. The total number of slots is 272 and the antenna size is 270.2 mm x 268.5 mm. Fig. 5 illustrates the top view of the whole antenna.

In Fig. 6, the measured return loss below -10dB is from 11.22 to 12.35 GHz. This antenna has a 9.4% bandwidth with a center frequency of 12 GHz. Fig. 7 shows the measured and simulated  $\underline{yz}$ -plane copolarization radiation patterns at 12 GHz, with the measured antenna gain being 20.32 dBi and the sidelobe level below -15 dB. The simulation results are obtained by the software *Ansoft* HFSS.

## 4. Conclusion

This paper presents a novel CBCPW slot array antenna with a slot array. Using appropriate tilt angles, proper arrangement of slots and other optimized parameters, the antenna has a high gain and a low sidelobe level. It is noticed that CBCPW can be used as an excellent antenna structure with its power leakage of the no-cutoff parallel-plate mode.

# Acknowledgments

The work was supported in part by the National Science Council under Grants NSC 95-2218-E-009-041 and NSC 95-2752-E-002-009, and in part by the Kinki Mobile Radio Center, Foundation under KMRC R&D Grant for Mobile Wireless.

# References

- H. Shigesawa, M. Tsuji, A. A. Oliner, "Conductor-backed slot line and coplanar waveguide: dangers and full-wave analyses," IEEE MTT-S International Microwave Symposium Digest, vol. 1, pp.199 – 202, May 25-27, 1988.
- [2] R. W. Jackson, "Mode conversion at discontinuities in finite-width conductor-backed coplanar waveguide," IEEE Transactions on Microwave Theory and Techniques, vol. 37, No. 10, pp. 1582-1589, Oct. 1989.
- [3] W. E. McKinzie, N. G. Alexopoulos, "Leakage losses for the dominant mode of conductorbacked coplanar waveguide," IEEE Microwave and Guided Wave Letters, vol. 2, No. 2, pp. 65-66, Feb. 1992.
- [4] Y. Liu, K. Cha, and T. Itoh, "Non-leaky coplanar (NLC) waveguides with conducting backing," IEEE Transaction on Microwave Theory Tech., vol. 43, no. 5, pp. 1067-1072, May 1995.
- [5] F. R. Yang, K. P. Ma, Y. Qian, and T. Itoh, "A uniplanar compact photonic-bandgap (UC-PBG) structure and its applications for microwave circuits," IEEE Transaction on Microwave Theory Tech., vol. 47, no. 8, pp. 1509-1514, Aug. 1999.
- [6] I.-C. Lan, P. Hsu, "Parallel-plate slot array fed by conductor-backed coplanar waveguide," European Microwave Conference, Paris, Vol. 1, Oct. 2005.
- [7] R. S. Elliott, Antenna theory and design, 2nd ed., John Wiley & Sons, Inc., 2003.
- [8] M. Ando, T. Numata, J.-I Takada, N. Goto, "A linearly polarized radial line slot antenna", IEEE Transactions on Antennas and Propagation, vol. 36, issue 12, pp. 1675-1680, Dec. 1988.
- [9] J. Gulick, G. Stern, R. S. Elliot, "The equivalent circuit of a rectangular-waveguide-fed longitudinal slot," Antennas and Propagation Society International Symposium 1986, vol. 24, pp. 685-668, Jun 1986.
- [10] R. Shavit, "Impedance characteristics of a slot antenna fed by a parallel plate waveguide," Microwave and Optical Technology Letters, vol. 14, No. 2, pp.126-128, February 1997.



Figure 1: The top view and the cross-sectional view of the antenna





Figure 3: The propagation directions of CBCPW mode and parallel-plate mode



Figure. 4 The normalized radiation resistance versus tilt angle



Figure 5: The slotted conductor-backed coplanar waveguide antenna



Figure 7: Measured and simulated radiation patterns at 12 GHz