# Analysis of a Polarization Converter Using a Full-Vectorial Fundamental Alternating-Direction Implicit Beam-Propagation Method

Jun Shibayama #1, Akio Yokomizo #2, Junji Yamauchi #3, Hisamatsu Nakano #4

# Faculty of Science and Engineering, Hosei University 3-7-2 Kajino-cho, Koganei, Tokyo 184-8584, Japan <sup>1</sup> shiba@hosei.ac.jp <sup>2</sup> akio.yokomizo.6h@stu.hosei.ac.jp <sup>3</sup> j.yma@hosei.ac.jp <sup>4</sup> hymat@hosei.ac.jp

*Abstract*—A simplified algorithm for the full-vectorial alternating-direction implicit beam-propagation method (FV-ADI-BPM) is developed using a fundamental scheme. The resultant equations are reduced to those with only two spatial derivatives for a polarization coupling effect in the right-hand sides, while the conventional FV-ADI-BPM includes four derivatives for a specific polarization and four for a polarization coupling effect. We assess the performance, when analyzing a *z*-variant structure with a polarization coupling effect. The present method is found to yield the result identical to that from the conventional method, reducing the computation time by about 35%.

## I. INTRODUCTION

Polarization converters have many applications, including polarization controllers, switches, and polarization diversity heterodyne receivers [1], [2]. To analyze the polarization converters, we have to use a full-vectorial (FV) method that can take polarization coupling effects into account. One of the most frequently used numerical methods for the FV analysis is the beam-propagation method (BPM) [3]-[6] based on the alternating-direction implicit (ADI) method [7], [8]. The ADI-BPM has become the de facto standard technique in commercial software packages due to its high efficiency.

Recently, a fundamental scheme has been developed for efficient implementations of implicit finite-difference timedomain (FDTD) methods [9], [10], such as the ADI-FDTD [11], [12] and the locally one-dimensional (LOD) FDTD. With the fundamental scheme, we obtain matrix-operator-free forms in the right-hand sides (RHSs) of the basic equations for the ADI- and LOD-FDTDs. We have applied the fundamental scheme to the frequency-dependent LOD-FDTD [13] and the body-of-revolution LOD-FDTD [14]. Note that the formulation of the ADI-FDTD parallels that of the ADI-BPM. We were therefore motivated to apply the fundamental scheme to efficient implementation of the semi-vectorial (SV) ADI-BPM [16]. Unfortunately, the SV-ADI-BPM cannot treat polarization coupling effects.

The purpose of this article is to develop a simple FV-ADI-BPM based on the fundamental scheme and investigate its effectiveness for the analysis of devices with a polarization coupling effect. First, we present the resultant FV equations based on the fundamental scheme, in comparison with those of the conventional equations. Next, to investigate the ability to treat *z*-variant structures with polarization coupling effects, we analyze a mode-evolution-based polarization converter [1]. Finally, we mention the efficiency improvement of the proposed FV-ADI-BPM.

## II. FV Equations Based on the Fundamental Scheme

The coupled Fresnel equations of the conventional FV-ADI-BPM [5] can be arranged to

$$\begin{pmatrix} 1 - \frac{\Delta z}{2} A_y \end{pmatrix} E_x^{l+1/2} = \left( 1 + \frac{\Delta z}{2} A_x \right) E_x^l + \frac{\Delta z}{2} C E_y^l$$

$$\begin{pmatrix} 1 - \frac{\Delta z}{2} B_y \end{pmatrix} E_y^{l+1/2} = \left( 1 + \frac{\Delta z}{2} B_x \right) E_y^l + \frac{\Delta z}{2} D E_x^{l+1/2}$$

$$(1b)$$

for the first step and

$$\left(1 - \frac{\Delta z}{2}B_x\right)E_y^{l+1} = \left(1 + \frac{\Delta z}{2}B_y\right)E_y^{l+1/2} + \frac{\Delta z}{2}DE_x^{l+1/2} \quad (2a)$$

$$\left(1 - \frac{\Delta z}{2}A_x\right)E_x^{l+1} = \left(1 + \frac{\Delta z}{2}A_y\right)E_x^{l+1/2} + \frac{\Delta z}{2}CE_y^{l+1} \quad (2b)$$

for the second step, in which  $A_x, A_y, B_x$ , and  $B_y$  represent spatial second derivatives for a specific polarization, including phase variation terms, and C and D represent spatial mixed derivatives for a polarization coupling effect. The detailed definitions for these notations are given in [5].

We here resort to the fundamental scheme for efficient implementation of (1) and (2). Introducing the auxiliary variables  $v_x, v_y, \phi_x$  and  $\phi_y$ , we finally obtain the simplified equations



Fig. 1. Schematic view of a mode-evolution-based polarization converter.

of the fundamental ADI-BPM (FADI-BPM) as follows:

$$v_x^{l} = 2E_x^{l} - v_x^{l-1/2} + \phi_y^{l}$$
(3a)  
(1  $\Delta z$ , )  $z_{l+1/2}^{l+1/2} = l$ (3a)

$$\left(1 - \frac{\Delta z}{2}A_y\right)E_x^{l+1/2} = v_x^l \tag{3b}$$

$$\phi_x^{l+1/2} = \frac{\Delta z}{2} D E_x^{l+1/2}$$
(3c)  
$$v^l - 2 E^l - v^{l-1/2} + \phi^{l+1/2}$$
(3d)

$$\left(1 - \frac{\Delta z}{2}B_y\right)E_y^{l+1/2} = v_y^l \tag{3e}$$

for the first step and

$$v_y^{l+1/2} = 2E_y^{l+1/2} - v_y^l + \phi_x^{l+1/2}$$
(4a)

$$\left(1 - \frac{\Delta z}{2}B_x\right)E_y^{l+1} = v_y^{l+1/2} \tag{4b}$$

$$\phi_y^{l+1} = \frac{\Delta z}{2} C E_y^{l+1} \tag{4c}$$

$$v_x^{l+1/2} = 2E_x^{l+1/2} - v_x^l + \phi_y^{l+1}$$
(4d)

$$\left(1 - \frac{\Delta z}{2}A_x\right)E_x^{l+1} = v_x^{l+1/2} \tag{4e}$$

for the second step. For the initial fields  $E_x^0$  and  $E_y^0$ , the algorithm requires the input initialization as

$$v_x^{-1/2} = \left(1 - \frac{\Delta z}{2}A_x\right)E_x^0\tag{5}$$

$$v_y^{-1/2} = \left(1 - \frac{\Delta z}{2}B_x\right)E_y^0.$$
 (6)

It is worth mentioning that (3) and (4) include only two spatial derivatives D and C for the polarization coupling effect in the RHSs, while the conventional method of (1) and (2) has four derivatives for the specific polarization and four for the polarization coupling effect in the RHSs. This fact leads to quite efficient implementation of the FV-BPM with fewer calculations of the spatial derivatives.



Fig. 2. Normalized powers of  $E_y$  and  $E_x$  fields.

## **III. NUMERICAL RESULTS**

To investigate the effectiveness of the FV-FADI-BPM, we analyze the mode-evolution-based polarization converter [1] shown in Fig. 1. The material and configuration parameters are as follows:  $n_{\rm co} = 2.2$ ,  $n_{\rm cl} = 1.445$ ,  $h = w_1 = 0.4 \ \mu {\rm m}$ ,  $w_2 = 0.8 \ \mu {\rm m}$  and  $l = 200 \ \mu {\rm m}$ . The numerical parameters are  $\Delta x = \Delta y = \Delta z = 0.02 \ \mu {\rm m}$ .

Fig. 2 shows the normalized powers of  $E_y$  and  $E_x$  fields at  $\lambda = 1.55 \ \mu m$  as a function of propagation distance. The fundamental TM mode is excited at the input port. As can be seen in Fig. 2, the TM mode (the  $E_y$  field) is converted into the TE mode (the  $E_x$  field). The calculated FADI results from (3) and (4) are found to show no appreciable difference at the scale of Fig. 2, relative to the conventional ADI results from (1) and (2). In fact, the difference of the two results is within the order of  $10^{-13}$ , demonstrating they are practically equivalent even for the z-variant structure with the polarization coupling effect. It is worth mentioning that the computation time of the FADI is reduced by 35% of that of the conventional method.

### IV. CONCLUSION

We have developed an efficient FV-ADI-BPM based on the fundamental scheme. The resultant equations are shown to be much simpler than those of the conventional FV-ADI-BPM, i.e., only two derivatives for a polarization coupling effect are calculated in the RHSs. The effectiveness of the developed method is investigated through the analysis of a polarization converter. Even for a *z*-variant structure, the developed method yields results identical to those of the conventional method, with reduced computation time.

## ACKNOWLEDGMENT

The authors thank Mr. Y. Wakabayashi of Hosei University for his assistance. This work was supported in part by MEXT, Grant-in-Aid for Scientific Research (c) (23560415).

#### References

- M. R. Watts and H. A. Haus, "Integrated mode-evolution-based polarization rotators," *Opt. Lett.*, vol. 30, no. 2, pp. 138-140, Jan. 2005.
- [2] J. Yamauchi, M. Yamanoue, and H. Nakano, "A short polarization converter using a triangular waveguide," J. Lightw. Technol., vol. 26, no. 12, pp. 1708-1714, Dec. 2008.
- [3] D. Yevick, M. Glasner, and B. Hermansson, "Numerical studies of split-operator finite-difference alternating-direction implicit propagation techniques based on generalized Padé approximants," *Opt. Lett.*, vol. 17, no. 10, pp. 725-727, May 1992.
- [4] J. Yamauchi, G. Takahashi, and H. Nakano, "Full-vectorial beampropagation method based on the McKee-Mitchell scheme with improved finite-difference formulas," *J. Lightw. Technol.*, vol. 16, no. 12, pp. 2458-2464, Dec. 1998.
- [5] Y. L. Hsueh, M. C. Yang, and H. C. Chang, "Three-dimensional noniterative full-vectorial beam propagation method based on the alternating direction implicit method," *J. Lightw. Technol.*, vol. 17, no. 11, pp. 2389-2397, Nov. 1999.
- [6] S. L. Chui and Y. Y. Lu, "Wide-angle full-vector beam propagation method based on an alternating direction implicit preconditioner," J. Opt. Soc. Am. A, vol. 21, no. 3, 420-425, Mar. 2004.
- [7] J. Yamauchi, T. Ando, and H. Nakano, "Beam-propagation analysis of optical fibres by alternating direction implicit method," *Electron. Lett.* vol. 27, no. 18, pp. 1663-1665, Aug. 1991.
- [8] J. Shibayama, T. Takahashi, J. Yamauchi, and H. Nakano, "A threedimensional horizontally wide-angle noniterative beam-propagation method based on the alternating-direction implicit scheme," *IEEE Photon. Technol. Lett.*, vol. 18, no. 5, pp. 661-663, Mar. 2006.
- [9] E. L. Tan, "Fundamental schemes for efficient unconditionally stable implicit finite-difference time-domain methods," *IEEE Trans. Antennas Propag.*, vol. 56, no. 1, pp. 170-177, Jan. 2008.
- [10] E. L. Tan, "Acceleration of LOD-FDTD method using fundamental scheme on graphics processor units," *IEEE Microw. Wireless Compon. Lett.*, vol. 20, no. 12, pp. 648-650, Dec. 2010.
- [11] T. Namiki, "A new FDTD algorithm based on alternating-direction implicit method," *IEEE Trans. Microw. Theory Tech.*, vol. 47, no. 10, pp. 2003-2007, Oct. 1999.
- [12] F. H. Zheng, Z. Z. Chen, and J. Z. Zhang, "A finite-difference timedomain method without the Courant stability conditions," *IEEE Microw. Guided Wave Lett.*, vol. 9, no. 11, pp. 441-443, Nov. 1999.
- [13] J. Shibayama, M. Muraki, J. Yamauchi, and H. Nakano, "Efficient implicit FDTD algorithm based on locally one-dimensional scheme," *Electron. Lett.*, vol. 41, no. 19, pp. 1046-1047, Sep. 2005.
- [14] J. Shibayama, T. Oikawa, J. Yamauchi, and H. Nakano, "Efficient LOD-BOR-FDTD implementation based on a fundamental scheme," *IEEE Photon. Technol. Lett.*, vol. 24, no. 11, pp. 957-959, Jun. 2012.
- [15] J. Shibayama, T. Hirano, J. Yamauchi, and H. Nakano, "Efficient implementation of frequency-dependent 3-D LOD-FDTD method using fundamental scheme," *Electron. Lett.*, vol. 48, no. 13, pp. 774-775, Jun. 2012.
- [16] J. Shibayama, A. Yokomizo, J. Yamauchi, and H. Nakano, "Reformulation of the ADI-BPM using a fundamental scheme," *IEICE Electron. Express*, vol. 9, no. 5, pp. 365-370, 10 Mar. 2012.