Simulation Accuracy of Normal-Mode Helical Antenna Used in Human Body

Nguyen Thanh Tuan¹, Yoshihide Yamada¹, Dang Tien Dung², Nguyen Quoc Dinh², Naobumi Michishita³
1: Malaysia-Japan International Institute of Technology, Universiti Teknologi Malaysia, Kuala Lumpur, Malaysia
2: Department of Fundamentals of Radio and Electronics Engineering, Le Quy Don Technical University, Hanoi, Vietnam 3: Department of Electrical and Electronics Engineering, National Defense Academy, Yokosuka, Japan

Abstract – Normal-Mode Helical Antenna (NMHA) is one of the promising antennas for implanted applications. Due to antennas put inside human body, electromagnetic simulations are needed to model human body and clarify electrical characteristics of antennas. In this paper, electromagnetic performances of NMHA were successfully clarified in human muscle condition by using Method of Moment (MoM) and Finite Element Method (FEM) scheme of a commercial electromagnetic simulator FEKO 7.0. Calculation results of MoM and FEM are compared to ensure simulation accuracy. Very good agreements between two simulation methods are obtained. By using correct simulation results, experimental results will be given.

Index Terms — NMHA, Human Body, FEKO, MoM, FEM

1. Introduction

Previously, some kind of antennas were proposed for medical applications [1][2][3]. However, in case of implanted applications, surrounding of antenna is human tissues in which consists of electrical constants as permittivity, conductivity or dielectric loss. Therefore, effects of dielectric on antenna performances should be studied. Normal-mode helical antennas (NMHA) are well-known that can achieve rather high antenna efficiencies at very small sizes almost 1/100 wavelength [4][5]. So, this antenna is applicable for vaio sensors of human body. In this study, a small NMHA and a part of human muscle are modeling and calculated at implanted applications frequency of 402 MHz by commercial electromagnetic simulator FEKO 7.0 [6].

Physical antenna performances such as electromagnetic field distributions, input impedances and radiation pattern can be adequately recognized. In order to clarify simulation accuracy, calculated results by Method of Moment (MoM) and Finite Element Method (FEM) are compared.

2. Simulation Methods

Simulation model is constructed on electromagnetic simulator FEKO with human muscle is modeled as dielectric cylinder as shown in Fig. 1. Electric constants and dielectric block sizes are set similar to practical human muscle at 402 MHz. NMHA is put inside dielectric with $\varepsilon_r = 53$, so wavelength in material (λ_g) = 102 mm. Simulation parameters are summarized in Table. 1. Different mesh sizes of material are applied to investigate accuracy of calculation.



Fig. 1 Simulation model

TABLE 1: Simulation parameters

Method	MoM	FEM
Frequency	402 MHz	402 MHz
Dielectric Constant	$\varepsilon_r = 53$	$\varepsilon_r = 53$
	$\sigma = 0.15 (S/m)$	$\sigma = 0.15 (S/m)$
Mesh size of	$\lambda_g/100$	λ _g /100
Antenna Wire		
Mesh size of	$\lambda_g/20$; $\lambda_g/40$;	$\lambda_g/20$; $\lambda_g/40$;
Material	$\lambda_g/50$	$\lambda_g/50$
Metallic wire	Copper	Copper
Memory	669 MB	1552 MB
Calculation time	0.46 h/ sim	0.24 h/ sim

3. Simulation Accuracy





Fig. 3 Resonant condition of FEM

A model is simulated with different material mesh sizes of $\lambda_g/20$; $\lambda_g/40$ and $\lambda_g/50$ to determine resonant condition. In both cases of MoM and FEM, resonant points of 402 MHz are convergent with material mesh sizes of $\lambda_g/40$ and $\lambda_g/50$. However, in case of $\lambda_g/20$, 402 MHz is not resonant point as shown in Fig. 2 and Fig. 3. Therefore, material mesh size of $\lambda_g/40$ is reliable and selected to save memory and calculation time. From resonant conditions, self-resonant structures of NMHA in human body are determined as presented in Fig. 4. MoM and FEM show a good agreement of self-resonant structures. Antenna diameters reduce in the increasing of number of turns (N) [7].

To ensure simulation accuracy, antenna performances of structure A in Fig. 4 are also investigated by MoM and FEM. Electric field distributions and radiation patterns of NMHA in human body are shown in Fig. 5 and Fig. 6, respectively. Very good agreements between two simulation methods are achieved. So, calculations of antenna performances can be considered correct.



Fig. 4 Self-resonant structures



(a) MoM (b) FEM Fig. 5 Electric field distributions



Conclusion

By using two simulation methods of MoM and FEM, antenna performances of NMHA used in human body can be confirmed. Experimental results will be given in the next study.

References

4.

- Toshihiro Kumagai, Kazuyuki Saito, Masaharu Takahashi, Koichi Ito, "A Small 915 MHz Receiving Antenna for Wireless Power Transmission Aimed ar Medical Applications", International Journal of Technology (2011) 1: 20-27, ISSN 2086-9614
- [2] Haiyu Huang, Karl Nieman, Ye Hu and Deji Akinwande, "Electrically Small Folded Ellipsoidal Helix Antenna for Medical Implant Applications", AP-S/URSI 2011 IEEE
- [3] Dmitriy D Karnaushenko, Daniil Karnaushenko, Denys Makarov and Oliver G Schmidt, "Compact helical antenna for smart implant applications", NPG Asia Materials (2015) 7, e188; doi:10.1038/am.2015.53
- [4] Won Gook Hong, Naobumi Michishita and Yoshihide Yamada, "Low-profile Normal-Mode Helical Antenna for Use in Proximity to Metal", ACES Journal, Vol.25, No.3, PP.190-198, March 2010
- [5] Quoc Dinh Nguyen, Naobumi Michishita, Yoshihide Yamada and Koji Nakatani, "Deterministic Equation for Self-Resonant Structures of Very Small Normal-Mode Helical Antennas", IEICE Trans.Commun., Vol.E94-B, No.5, PP.1276-1279, May 2011
- [6] FEKO suite 7, EM Software & Systems
- [7] Nguyen Thanh Tuan, Yoshihide Yamada, Nguyen Quoc Dinh, Naobumi Michishita, "Self-Resonant Structures of Normal-Mode Helical Antennas embedded in Dielectric and Magnetic Materials", ATC, 627-632, ISSN 2162-1020, Oct 2015.