

RECENT ADVANCES IN FAST SOLVERS FOR COMPUTATIONAL ELECTROMAGNETICS

W.C. Chew, J.M. Jin, E. Michielssen, J. Schutt-Aine,
 J.M. Song, J.S. Zhao, S. Velampambil, H.Y. Chao,
 Center for Computational Electromagnetics
 Department of Electrical and Computer Engineering
 University of Illinois
 Urbana, IL 61801-2991
 Email:w-chew@uiuc.edu

Introduction

Due to the rapid advances in computer technology, increasing amount of electromagnetic analysis is performed using computational electromagnetics. However, traditional computational algorithms are slow and memory inefficient. Our Center has focused on developing fast solvers which are both memory and CPU efficient. These fast solvers permit the solution of problems of unprecedented sizes using existing computers. Method of moments problems with about 10 million unknowns have been solved as a result [1]. More recently, these fast solvers have been parallelized, and generalized to very low frequency applications [2,3]. This talk will discuss these advances.

Large Scale Computing with MLFMA

The MLFMA (multilevel fast multipole algorithm) for electrodynamics is developed at the University of Illinois for large scale computing of scattering by large electromagnetic targets [4-7]. Its working principle is based on telephone network communication. When an integral equation is solved by the method of moments, all current elements on the scatterer communicate to each other via a matrix-vector multiplication. A straight-forward way of performing a matrix-vector product is similar to connecting N telephones together via direct links. The number of links is proportional to N^2 . Therefore, it is necessary to reduce the number of links via a multilevel approach, as in done in a telephone network.



Figure 1. The analogy of a matrix-vector multiplication to a telephone network. The left picture shows a straightforward matrix-vector product, where the number of links is enormous. The right shows a two-level matrix vector product where the number of links is greatly reduced.

In the two-level approach, the scattering elements are organized into groups according to their physical proximity. The information from nearby sources are aggregated into the hub at the center of the group. Then, the information is transferred from group to group via the hubs. Evidently, the number of links are reduced. In order to facilitate the two-stage communication of information, a matrix element has to be factorized as

$$A_{ij} = \bar{V}'_{il} \bullet \bar{T}_{ll'} \bullet \bar{V}'_{rj}$$

where $\bar{T}_{ll'}$, the translation matrix, is a diagonal matrix. The diagonalization of the translation matrix is first achieved by Rokhlin [8]. In this manner, the computational complexity of a matrix-vector multiplication is reduced to $N^{1.5}$.




Figure 2. A multilevel tree structure for transferring information between current elements in a scatterer. As a consequence, the information can be transferred in $N \log N$ operations.


The idea of a two-level algorithm can be generalized to a multilevel approach where a matrix element has to be factorized

as:

$$A_{ij} = \bar{V}'_{i l_1} \bullet \bar{\beta}_{l_1 l_2} \bullet \bar{\beta}_{l_2 l_3} \cdots \bar{\beta}_{l_{L-1} l_L} \bullet \bar{T}'_{l''} \bullet \bar{\beta}_{l_L l_{L-1}} \cdots \bar{\beta}_{l_3 l_2} \bullet \bar{\beta}_{l_2 l_1} \bullet \bar{V}'_{l' j}$$

The workload at the higher-level can be reduced by interpolation and antepolation. In this manner, the workload at each level can be kept to $O(N)$. Since there are $\log(N)$ levels in the tree, a matrix-vector product can be performed in $O(N \log N)$ operations.


Figure 3. In three dimension, the scatterer is enclosed in a box, which is recursively subdivided into smaller boxes until the smallest one contains only a few current elements. An oct-tree network is set up to facilitate information transfer in $N \log N$ operations.



For three-dimensions, the scatterer is first embedded in an enclosing box. The box is recursively divided into eight smaller boxes until the smallest one contains about one or two subscattering elements. Then an abstract oct-tree communication network is established within the computer to facilitate a matrix-vector product to be effected in $O(N \log N)$ operations.

As a consequence, the fast way of performing a matrix-vector product can be substituted into a iterative matrix solver such as the conjugate gradient (CG) solver. When CG is applied to solve a dense matrix system arising from the method of moments, the bottleneck of computation is the matrix-vector product. A traditional approach of invoking a matrix-vector product is of $O(N^2)$ in CPU time and memory. However, with the fast solvers, it can be invoked in $O(N \log N)$ operations. The method is also matrix free, bypassing the need to generate the matrix in the solution process. Consequently, the memory requirements of such an algorithm is greatly reduced. This phenomenal reduction in memory requirements and CPU time illustrates the cruelty of computational complexity. For large problems, the memory requirements and CPU time can be orders of magnitude larger as illustrated in Table 1.

Bistatic RCS of VFY218 at 3 GHz
8 processors of SGI Origin 2000
of Unknowns $N = 2$ millions



	Memory (GB)	Matrix Fill (days)	LUD (years)	One-RHS (hrs)
FISC	5	0.1		9
LUD	32,000	600.0	200	4
CG	32,000	600.0		500

Table 1. Resources needed for FISC (Fast Illinois Solver Code) for 2 million unknowns when solving the VFY218 full size aircraft at 3 GHz. This problem is practically unsolvable using conventional methods like LUD (lower and upper triangular decomposition) and CG (conjugate gradient). The problem was solved on 8 processors of SGI Origin 2000. (RHS-right hand side.)

Advanced Applications

With the availability of the geometry files, electromagnetic analysis now can be easily performed with these fast solvers. Figure 4 illustrates the computational of the electromagnetic interaction with the car.




Figure 4. The left geometry file is from VRML (virtual reality modeling language). The middle geometry file has undergone automatic mesh refinement to be electromagnetically compatible. The right figure illustrates the calculation of the interaction of a Hertzian dipole with the car.




Figure 5. The use of fast solvers for EMC/EMI applications in studying the leakage of electromagnetic signals from computer chassis.

These solvers have also been applied for EMC/EMI studies to ascertain the leakage of electromagnetic signals from computer chassis as shown in Figure 5.




Figure 6. The application of fast solvers for circuits from very low frequencies (static) to microwave frequencies.




Figure 7. The load balancing of a parallelized version of MLFMA called ScaleME. The right picture shows the physical configuration of a Linux cluster that it runs on.

Other Algorithm Developments

Recently, we have developed a low-frequency MLFMA (LF-MLFMA) that is stable at very low frequencies as well as microwave frequencies. It has been used to model an inductor in a micro-circuit as illustrated in Figure 6.

The MLFMA has also been parallelized into a code called ScaleME. The code has been able to solve a problem up to 4 million unknowns on an SGI O2K, while it can solve a 600,000 unknown problem on a Linux cluster costing \$15,000. Figure 7 shows the load balancing of ScaleME running on such a cluster. These algorithms have also been replicated in the time domain [9,10]. Moreover, higher order versions of these algorithms have been developed [11]. Also, fast algorithms have been developed for layered media [12,13].

Bibliography

1. "New Algorithms Lead to Breakthrough Simulations on NCSA Supercomputer," *NCSA News Release, March 14, 2000*, <http://access.ncsa.uiuc.edu/Headlines/00Headlines/000314.Algorithms.html>. Also, "Fast and efficient algorithms handle nearly 10 million unknowns," *News From the University of Illinois at Urbana-Champaign*, November 1999, <http://www.ccem.uiuc.edu>, or <http://www.oc.uiuc.edu/NB/99.11/computerstip.html>.
2. S. V. Velamparambil, J. E. Schutt-Aine, J. G. Nickel, J. M. Song and W. C. Chew, "Solving large scale electromagnetic problems using a linux cluster and parallel MLFMA," *IEEE Antennas and Propagation Society International Symposium*, Orlando, Florida, vol. 1, pp. 636-639, July 11-16, 1999.
3. J. S. Zhao, W. C. Chew, "Integral Equation Solution of Maxwell's Equations from Zero Frequency to Microwave Frequencies," accepted for publication in James R. Wait Memorial Special Issue, *IEEE Trans. Antennas Propag.*, August 2000.
4. C. C. Lu and W. C. Chew, "A fast algorithm for solving hybrid integral equations," *IEE Proceedings-H*, vol. 140, no. 6, pp. 455-460, Dec. 1993.
5. C. C. Lu and W. C. Chew, "A multilevel algorithm for solving the boundary integral equation of scattering," *Micro. Opt. Tech. Lett.*, vol. 7, no. 10, pp. 466-470, July 1994.
6. J. M. Song and W. C. Chew, "Multilevel fast multipole algorithm for solving the combined field integral equation of electromagnetic scattering," *Mico. Opt. Tech. Lett.*, vol. 10, no. 1, pp. 14-19, Sept. 1995.
7. J. M. Song, C.-C. Lu, and W. C. Chew, "MLFMA for electromagnetic scattering by large complex objects," *IEEE Trans. Ant. Propag.*, vol. 45, no. 10, pp. 1488-1493, Oct. 1997.
8. V. Rokhlin, "Rapid solution of integral equations of scattering theory in two dimensions," *Journal of Computational Physics*, vol. 86, no. 2, p. 414, 1990.
9. A. Ergin, B. Shanker, E. Michielssen, "Fast evaluation of three-dimensional transient wave fields using diagonal translation operators," *Journal of Computational Physics*, vol. 146, no. 1, pp. 157-180, October 10, 1998.
10. A. Ergin, B. Shanker, and E. Michielssen, "The plane wave time domain algorithm for the fast analysis of three-dimensional wave fields," *IEEE Antennas Propag. Mag.*, vol. 41, no. 4, pp. 39-52, Aug. 1999.
11. K. C. Donopudi, J. M. Jin, S. Velamparambil, J. M. Song, and W. C. Chew, "Parallelized higher-order multilevel fast multipole algorithm for 3D scattering," *IEEE Trans. Antennas Propag.*, submitted for publication, 1999.
12. B. Hu and W. C. Chew, "Fast Steepest Descent Path Algorithm for Electromagnetic Scattering Problems in Layered Medium," *IEEE Antennas and Propagation Society International Symposium*, Orlando, Florida, vol. 2, pp. 1182-1185, July 11-16, 1999.
13. F. Ling, J.M. Song, and J.M. Jin, "Multilevel fast multipole algorithm for analysis of large-scale microstrip structures," *Microwave and Guided Wave Letters*, vol. 9, no. 12, pp. 508-510, December, 1999.