B_{-9-4} DIFFRACTION OF A PLANE ELECTROMAGNETIC WAVE BY A PAIR OF PARALLEL, SEMI-INFINITE SCREENS WITH SURFACE IMPEDANCE

Toshio WAKABAYASHI and Yoshio MIHARA

Tokai University Hiratsuka, Kanagawa, Japan

Introduction 1

The diffraction of a plane electromagnetic wave by an imperfectly conducting sheet is an important problem for the electromagnetic wave propagation in the city and the antenna theory. This paper describes the diffraction by a pair of parallel, semi-infinite screens with surface To analyze such a problem, we use the angular spectrum method impedance. which is easier than others and is also useful for the diffraction problems.", (2), (3)

2 Analysis

2

Let us consider that the problem is two dimensional case. As shown in Fig.1, S1 and S2 are imperfectly conducting screens with equal surface impedance $\frac{1}{2} \mathbb{Z}_{\circ}(\mathbb{Z}_{\circ} = [\mu_{\circ}/\varepsilon_{\circ}])$ which are occupying y=0, x>0, and y=a, x>0 in a r free space region (\mathcal{E}_{\circ} , μ_{\circ}), respectively. It is assumed that their thickness \mathcal{T} satisfies that $\lambda \gg \tau \gg d$, where λ_0 is the free space wavelength and d is the penetration depth.

(1)

Consider an incident plane wave with E-polarization given by $E_{z}^{i} = e^{ik_{o}r\cos(\theta - \alpha_{o})}$

where the time factor exp(-iwt) is suppressed throughout, $k_o = \omega (2_0 \mu_0 = 2\pi / \lambda_o$, and α_o is real and $0 < \alpha_o < \pi$. Then, using the angular spectra $P(k,\omega\alpha)$'s, the scattered fields due to induced currents in S1 and S2 may be written as follows



Fig.1 Geometry of the problem

$$E_{z}^{sir} = \int_{C^{r}} P^{ir}(k_{o}\cos\alpha) e^{ik_{o}r\cos(\theta+\alpha)} d\alpha, \quad (y<0), \quad (2)$$

$$E_{z}^{sit} = \int_{C^{t}} P^{it}(k_{o}\cos\alpha) e^{ik_{o}r\cos(\theta - \alpha)} d\alpha, \quad (y>0), \quad (3)$$

$$E_{Z}^{s2r} = \int_{C^{r}} P^{2r}(k_{o} \cos \alpha) e^{i k_{o} r' \cos (\theta' + \alpha)} d\alpha', \quad (y < \alpha), \quad (4)$$

$$E_{z}^{s2t} = \int_{\mathcal{C}^{t}} P^{2t}(k_{o}\cos\alpha) e^{i \cdot k_{o}r'\cos(\theta' - \alpha)} d\alpha, \quad (y > \alpha), \quad (5)$$

-323-

where when we transform the above equations by $\lambda = k_{\circ} \cos \alpha$, C^r and C^t are the integral paths in the complex α -plane coinciding with the real axis in the complex λ -plane.

The total fields \mathbf{E} and \mathbf{H} are expressed as follows

$$\mathbf{E} = \mathbf{E}^{4} + \mathbf{E}^{51} + \mathbf{E}^{52}, \quad \mathbf{H} = \mathbf{H}^{4} + \mathbf{H}^{51} + \mathbf{H}^{52}. \tag{6}$$

At the two screens the boundary condition is

$$\mathbf{E} - (\mathbf{M} \cdot \mathbf{E})\mathbf{n} = \mathbf{\eta} \mathbf{Z}_{\bullet} \mathbf{n} \times \mathbf{H}, \qquad (7)$$

where n is the unit vector outwared normal. Furthermore, the tangential components of scattered fields should be continuous across the regions y=0, x <0 and y=a, x <0.

After changing the variable from \propto to $\lambda = k_{out} \alpha'$, we obtain the integral equations on the angular spectra from the boundary conditions. For example, for x > 0,

$$\int_{-\infty}^{\infty} \left(\frac{P^{ir}(\lambda)}{\sqrt{k_o^2 - \lambda^2}} + \frac{P^{2t}(\lambda)}{\sqrt{k_o^2 - \lambda^2}} + \left\{ \frac{P^{it}(\lambda)}{\sqrt{k_o^2 - \lambda^2}} + \frac{P^{2r}(\lambda)}{\sqrt{k_o^2 - \lambda^2}} \right\} e^{i\alpha\sqrt{k_o^2 - \lambda^2}} \right) \times \left(1 + \frac{\gamma Z_o}{\omega\mu_o} \sqrt{k_o^2 - \lambda^2} \right) e^{i\chi\lambda} d\lambda = -F_{(-)}(\lambda_o) e^{i\chi\lambda_o}, \quad (8)$$

$$\int_{-\infty}^{\infty} \left(\frac{P^{\text{Ir}}(\lambda)}{\sqrt{k_o^2 - \lambda^2}} - \frac{P^{2t}(\lambda)}{\sqrt{k_o^2 - \lambda^2}} - \left\{ \frac{P^{1t}(\lambda)}{\sqrt{k_o^2 - \lambda^2}} - \frac{P^{2r}(\lambda)}{\sqrt{k_o^2 - \lambda^2}} \right\} e^{i\alpha \sqrt{k_o^2 - \lambda^2}} \right) \\ \times \left(1 + \frac{\frac{\eta Z_o}{\omega \mu_o}}{\frac{\pi^2}{k_o^2 - \lambda^2}} \right) e^{i\chi\lambda} d\lambda = -G_{(-)}(\lambda_o) e^{i\chi\lambda_o} , \qquad (9)$$

$$\int_{-\infty}^{\infty} \left\{ \frac{P^{it}(\lambda)}{\sqrt{k_o^2 - \lambda^2}} + \frac{P^{2r}(\lambda)}{\sqrt{k_o^2 - \lambda^2}} \right\} F_{(+)}(\lambda) e^{i \chi \lambda} d\lambda = -F_{(+)}(\lambda_0) e^{i \chi \lambda_0}, \quad (10)$$

$$\int_{-\infty}^{\infty} \left\{ \frac{P^{tt}(\lambda)}{\sqrt{k_{\circ}^{2} - \lambda^{2}}} - \frac{P^{2r}(\lambda)}{\sqrt{k_{\circ}^{2} - \lambda^{2}}} \right\} \left(q_{(+)}(\lambda) e^{i\chi\lambda} d\lambda = - \left(q_{(+)}(\lambda_{\circ}) e^{i\chi\lambda_{\circ}} \right), \quad (11)$$

where

$$\overline{H}_{(\pm)}(\lambda) = | + e^{i \left(\lambda \sqrt{k_o^2 - \lambda^2} \pm \frac{7 Z_o}{\omega \mu_o} \sqrt{k_o^2 - \lambda^2} \right)} + e^{i \left(\lambda \sqrt{k_o^2 - \lambda^2} + \frac{7 Z_o}{\omega \mu_o} \sqrt{k_o^2 - \lambda^2} \right)},$$
(12)

$$G_{(\pm)}(\lambda) = |-e^{i\alpha\sqrt{k_o^2 - \lambda^2}} \pm \frac{\frac{\eta Z_o}{\omega\mu_o}}{\sqrt{k_o^2 - \lambda^2}} (1 + e^{i\alpha/k_o^2 - \lambda^2}), \quad (13)$$

 $P(\lambda)$'s are determined by solving these equations exactly. For example, the solutions are

$$P^{tt}(\lambda) = - \frac{\sqrt{\frac{1}{4}\lambda^2 - \lambda^2}}{4\pi i (\lambda - \lambda_o)} \overline{V}^{tt}(\lambda) , \quad P^{2t}(\lambda) = \frac{\sqrt{\frac{1}{4}\lambda^2 - \lambda^2}}{4\pi i (\lambda - \lambda_o)} \overline{V}^{2t}(\lambda) , \quad (14)$$

where

$$\nabla^{\prime t}(\lambda) = \frac{F_{(*)}(\lambda_{0})}{F_{(*)}(\lambda)} e^{f_{1+}(\lambda_{0}) - f_{1+}(\lambda)} + \frac{G_{(*)}(\lambda_{0})}{G_{(*)}(\lambda)} e^{f_{2+}(\lambda_{0}) - f_{2+}(\lambda)},$$
(15)

$$\nabla^{2t}(\lambda) = \nabla^{1t}(\lambda) e^{i\alpha \left[\frac{1}{h_0^2 - \lambda^2}} - \frac{F_{(-)}(\lambda_0) e^{\frac{1}{f_{1+}}(\lambda_0) - \frac{1}{f_{1+}}(\lambda)} - \frac{1}{f_{(-)}(\lambda_0) e^{\frac{1}{f_{2+}}(\lambda_0) - \frac{1}{f_{2+}}(\lambda)}}{(\omega \mu_0 + \frac{1}{7} Z_0 \sqrt{\frac{1}{h_0^2 - \lambda^2}}) / \omega \mu_0}, \quad (16)$$

and exp $\{-f_{1+}(\lambda)\}$ and exp $\{-f_{2+}(\lambda)\}$ are the functions which are regular and non-zero in the upper half-plane of λ

Numerical example 3

We can obtain the total field E_a^{t} (y>a) from Eqs. (1), (3), (5), (6) and (14). If we apply the steepest descent method to E_a^{t} , the asymptotic expressions for E_a^{t} are derived. For example, E_a^{t} for θ, θ' $> \alpha_0$ is written by

$$E_{z}^{t} \sim e^{i \cdot k_{o} \gamma \cdot co_{3}(\theta - \alpha_{o})} - \frac{sin \theta}{4\pi i (co_{3}\theta - co_{3}\alpha_{o})} \nabla^{t} (k_{o}co_{3}\theta) \sqrt{\frac{2\pi}{k_{o}r}} e^{i \cdot k_{o} \gamma - i \frac{\pi}{4}} + \frac{sin \theta'}{4\pi i (co_{3}\theta' - co_{3}\alpha_{o})} \nabla^{2t} (k_{o}co_{3}\theta') \sqrt{\frac{2\pi}{k_{o}r'}} e^{i \cdot k_{o}r' - i \frac{\pi}{4}}, \quad (17)$$

and for θ , $\theta' \sim d_0$,

$$E_{z}^{t} \sim \frac{1}{2} \left\{ 1 - C(w) - S(w) - i \left\{ S(w) - C(w) \right\} \right\}$$

$$\times e^{i k_{0} r \cos(\theta - \alpha_{0})}, \qquad (18)$$

where C(w) and S(w) are Fresnel integrals, and

$$W = \int \frac{\mathbf{k}_{o}r}{\pi} \cos\left(\theta - \alpha_{o}\right) \, \tan\left(\alpha_{o} - \theta\right) \tag{19}$$

The numerical results of $|\mathbf{E}_{\mathbf{z}}^{\mathbf{r}}|$ are shown in Fig.2, where the observation point is $P(\gamma', \theta')$.

Conclusion 4

It has been shown that the scattered fields when E-polarized plane wave is incident can be solved exactly, and the numerical results for $|E_{B}^{t}|$ have been compared with the case of one screen.

References

- T. B. A. Senior: Radio Science, 10, 6, 645-650(1975).
 G. D. Maliuzhinets: Sov. Phys. Dok1., 3, 752-755(1959).
 P. C. Clemmow: Proc. Roy. Soc. A, 205, 286-308(1951).



Fig.2 Numerical results for $|\mathbf{E}_{\mathbf{F}}^{t}|$.